

Chapter Five

5.Conclusion and recommendation

5.1 Conclusion

In this thesis it is clearly appears that the more number of antennas in the base station the more energy efficiency and area throughput, and the transmit power per base station decrease as the number of antenna increase. Contrary to common belief, the transmit power should increase with M. This indicates that massive MIMO can be built using low-power consumer grade transceiver equipment at the BSs instead of conventional industry-grade high-power equipment. The EE (in bit/Joule) is a quasi-concave function of M and K, thus it has a finite global optimum. Our numerical results show that deploying 100–200 antennas to serve a relatively large number of UEs is the EE-optimal solution using today’s circuit technology, we conclude that massive MIMO is the EE-optimal architecture.

5.2 Recommendation

As massive MIMO is still a relatively new research area in wireless communications, there are many topics for future work, including theoretical investigations, propagation measurements and implementation issues.

Regarding new channel measurements, outdoor-to-indoor scenarios are particularly interesting, as indoor coverage from outdoor base stations is a challenge for the operators. Massive MIMO is far from fully-exploited. With respect to propagation channels in real-life environments, there are many interesting aspects to study, and there are many new possibilities that have not been exploited yet.

investigate the performance of linear pre-coding techniques by taking into account the imperfect channel state information (CSI) and to Study the nonlinear pre-coding techniques for massive MIMO system. Compare the performance the linear and non

linear pre-coding techniques for massive MIMO system. Study the linear pre-coding techniques by taking into account pilot contamination phenomena.

On “massive” uses of the spatial domain, personally, I foresee a promising future of this technology.

REFERENCES

- [1] G. Auer and et al., D2.3: Energy efficiency analysis of the reference systems, areas of improvements and target breakdown. INFSO-ICT-247733 EARTH, ver. 2.0, 2012. [Online]. Available: <http://www.ict-earth.eu/>
- [2] Y. Chen, S. Zhang, S. Xu, and G. Li, “Fundamental trade-offs on green wireless networks,” IEEE Commun. Mag., vol. 49, no. 6, pp. 30–37, 2011.
- [3] “Smart 2020: Enabling the low carbon economy in the information age,” The Climate Group and Global e-Sustainability Initiative (GeSI), Tech. Rep., 2008.
- [4] Green Touch Consortium, Tech. Rep. [Online]. Available: <http://www.greentouch.org>
- [5] S. Tombaz, A. Västberg, and J. Zander, “Energy- and cost-efficient ultrahigh-capacity wireless access,” IEEE Wireless Commun. Mag., vol. 18, no. 5, pp. 18–24, 2011
- [6] E. Björnson, J. Hoydis, M. Kountouris, and M. Debbah, “Massive MIMO systems with non-ideal hardware: Energy efficiency, estimation, and capacity limits,” IEEE Trans. Inf. Theory, vol. 60, no. 11, pp. 7112–7139, 2014.
- [7] T. Marzetta, “Noncooperative cellular wireless with unlimited numbers of base station antennas,” IEEE Trans. Wireless Commun., vol. 9, no. 11, pp. 3590–3600, 2010.
- [8] F. Rusek, D. Persson, B. Lau, E. Larsson, T. Marzetta, O. Edfors, and F. Tufvesson, “Scaling up MIMO: Opportunities and challenges with very large arrays,” IEEE Signal Process. Mag., vol. 30, no. 1, pp. 40–60, 2013.
- [9] J. Hoydis, S. ten Brink, and M. Debbah, “Massive MIMO in the UL/DL of cellular networks: How many antennas do we need?” IEEE J. Sel. Areas Commun., vol. 31, no. 2, pp. 160–171, 2013.

- [10] H. Ngo, E. Larsson, and T. Marzetta, “Energy and spectral efficiency of very large multiuser MIMO systems,” *IEEE Trans. Commun.*, vol. 61, no. 4, pp. 1436–1449, 2013.
- [11] G. Miao, “Energy-efficient uplink multi-user MIMO,” *IEEE Trans. Wireless Commun.*, vol. 12, no. 5, pp. 2302–2313, 2013.
- [12] Y. Hu, B. Ji, Y. Huang, F. Yu, and L. Yang, “Energy-efficiency resource allocation of very large multi-user MIMO systems,” *Wireless Netw.*, 2014.
- [13] E. Björnson, M. Kountouris, and M. Debbah, “Massive MIMO and small cells: Improving energy efficiency by optimal soft-cell coordination,” in *Proc. Int. Conf. Telecommun. (ICT)*, 2013.
- [14] D. Ha, K. Lee, and J. Kang, “Energy efficiency analysis with circuit power consumption in massive MIMO systems,” in *Proc. IEEE Int. Symp. Personal, Indoor and Mobile Radio Commun. (PIMRC)*, 2013.
- [15] H. Yang and T. Marzetta, “Total energy efficiency of cellular large scale antenna system multiple access mobile networks,” in *Proc. IEEE Online Conference on Green Communications (OnlineGreenComm)*, 2013.
- [16] S. Mohammed, “Impact of transceiver power consumption on the energy efficiency spectral efficiency tradeoff of zero-forcing detector in massive MIMO systems,” 2014, submitted. [Online]. Available: <http://arxiv.org/abs/1401.4907v1>
- [17] E. Björnson and E. Jorswieck, “Optimal resource allocation in coordinated multi-cell systems,” *Foundations and Trends in Communications and Information Theory*, vol. 9, no. 2-3, pp. 113–381, 2013.
- [18] P. Zetterberg, “Experimental investigation of TDD reciprocity-based zero-forcing transmit precoding,” *EURASIP J. on Adv. in Signal Process.*, Jan. 2011.
- [19] C. Shepard, H. Yu, N. Anand, L. Li, T. Marzetta, R. Yang, and L. Zhong, “Argos: Practical many-antenna base stations,” in *Proc. ACM MobiCom*, 2012.
- [20] Further advancements for E-UTRA physical layer aspects (Release 9).

3GPP TS 36.814, Mar. 2010.

- [21] X. Gao, O. Edfors, F. Rusek, and F. Tufvesson, “Massive MIMO in real propagation environments,” *IEEE Trans. Wireless Commun.*, 2014, submitted. [Online]. Available: <http://arxiv.org/abs/1403.3376>
- [22] S. Pillai, T. Suel, and S. Cha, “The Perron-Frobenius theorem: some of its applications,” *IEEE Signal Process. Mag.*, vol. 22, no. 2, pp. 62–75, 2005.
- [23] A. Wiesel, Y. Eldar, and S. Shamai, “Linear precoding via conic optimization for fixed MIMO receivers,” *IEEE Trans. Signal Process.*, vol. 54, no. 1, pp. 161–176, 2006.
- [24] H. Boche and M. Schubert, “A general duality theory for uplink and downlink beamforming,” in Proc. IEEE VTC-Fall, 2002, pp. 87–91.
- [25] Y.-G. Lim, C.-B. Chae, and G. Caire, “Performance analysis of massive MIMO for cell-boundary users,” *IEEE J. Sel. Topics Signal Process.*, 2013, submitted. [Online]. Available: <http://arxiv.org/abs/1309.7817>
- [26] S. Cui, A. Goldsmith, and A. Bahai, “Energy-efficiency of MIMO and cooperative MIMO techniques in sensor networks,” *IEEE J. Sel. Areas Commun.*, vol. 22, no. 6, pp. 1089–1098, 2004.
- [27] A. Mezghani and J. A. Nossek, “Power efficiency in communication systems from a circuit perspective,” in Proc. IEEE Int. Symp. Circuits and Systems (ISCAS), 2011, pp. 1896–1899.
- [28] R. Kumar and J. Gurugubelli, “How green the LTE technology can be?” in Proc. Wireless VITAE, 2011.
- [29] S. Boyd and L. Vandenberghe, “Numerical linear algebra background.” [Online]. Available: www.ee.ucla.edu/ee236b/lectures/num-lin-alg.pdf
- [30] S. Mukherjee and S. Mohammed, “On the energy-spectral efficiency trade-off of the MRC receiver in massive MIMO systems with transceiver power consumption,” 2014. [Online]. Available: <http://arxiv.org/abs/1404.3010>
- [31] A. Hoofdar and M. Hassani, “Inequalities on the Lambert W function and hyperpower function,” *J. Inequalities in Pure and Applied Math.*,

- vol. 9, no. 2, pp. 1–5, 2008.
- and hyperpower function,” J. Inequalities in Pure and Applied Math., vol. 9, no. 2, pp. 1–5, 2008.
- [32] F. Shmakov, “A universal method of solving quartic equations,” Int. J. Pure and Applied Math., vol. 71, no. 2, pp. 251–259, 2011.
- [33] D. Kang, D. Kim, Y. Cho, J. Kim, B. Park, C. Zhao, and B. Kim, “1.6–2.1 GHz broadband doherty power amplifiers for LTE handset applications,” in Proc. IEEE MTT-S Int. Microwave Symp. Digest, 2011.
- [34] S. Tombaz, K. Sung, and J. Zander, “Impact of densification on energy efficiency in wireless access networks,” in Proc. IEEE Global Commun. Conf. (GLOBECOM), 2012.
- [35] M. Parker, “High-performance floating-point implementation using FPGAs,” in Proc. IEEE MILCOM, 2009.
- [36] E. Björnson, L. Sanguinetti, J. Hoydis, and M. Debbah, “Designing multi-user MIMO for energy efficiency: When is massive MIMO the answer?” in Proc. IEEE Wireless Commun. and Networking Conf. (WCNC), 2014.
- [37] H. Huh, G. Caire, H. Papadopoulos, and S. Ramprashad, “Achieving “massive MIMO” spectral efficiency with a not-so-large number of antennas,” IEEE Trans. Wireless Commun., vol. 11, no. 9, pp. 3226–3239, 2012.
- [38] H. Kim, C.-B. Chae, G. de Veciana, and R. Heath, “A cross-layer approach to energy efficiency for adaptive MIMO systems exploiting spare capacity,” IEEE Trans. Wireless Commun., vol. 8, no. 8, pp. 4264–4275, 2009.
- [39] D. Maiwald and D. Kraus, “Calculation of moments of complex Wishart and complex inverse Wishart distributed matrices,” IEE Proc. Radar Sonar Navig., vol. 147, no. 4, pp. 162–168, 2000.
- [40] S. Boyd and L. Vandenberghe, Convex Optimization. Cambridge University Press, 2004.
- [41] E. Björnson and B. Ottersten, “A framework for training-based estimation

in arbitrarily correlated Rician MIMO channels with Rician disturbance,” IEEE Trans. Signal Process., vol. 58, no. 3, pp. 1807–1820, 2010..

Appendix

```

%Initialization
close all;
clear all;

%%Simulation parameters

rng('shuffle'); %Initiate the random number generators with a random seed
%%If rng('shuffle') is not supported by your Matlab version, you can use
%%the following commands instead:
%randn('state',sum(100*clock));

%Ranges of optimization parameters
Mmax = 220; %Consider all number of BS antennas from 1 to 220 in simulation
Kmax = 150; %Consider all number of active UEs from 1 to 150 in simulation

%Should Monte Carlo simulations be used for MRT/MRC processing? (true or false)
runMonteCarloSimulationsMRT = true;

%Should Monte Carlo simulations be used for MMSE processing? (true or false)
%Beware: This part of the simulation is extremely slow, due to the iterative
%power allocation algorithm! It takes weeks to finish.
runMonteCarloSimulationsMMSE = false;

%Should the sequential/alternating optimization algorithm from Section V.E
%be used? (true or false). This option should only be turned on if the
%global optimum is within the range 1,...,Mmax and 1,...,Kmax, otherwise
%there will be an error.
runSequentialAlgorithm = true;

%Geometric scenarios (From Table 2)
d_max = 250; %Cell radius for a circular cell in the single-cell scenario. It is also the distance
from BS to a side of the square cells in the multi-cell scenario
d_min = 3; %Minimum distance between UE and BS
areaSinglecell = pi*(d_max/1000).^2; %Coverage area in km^2
areaMulticell = 4*(d_max/1000).^2; %Coverage area in km^2

%Large-scale fading parameters (From Table 2)
dbar = 10^(-3.53); %Regulates channel attenuation at minimum distance (see Example 1)
kappa = 3.76; %Path-loss exponent (see Example 1)

%Spectral resources and properties (From Table 2)
B = 20e6; %Transmission bandwidth (Hz)
Bc = 180e3; %Channel coherence bandwidth (Hz)
Tc = 10e-3; %Channel coherence time (s)
U = Bc * Tc; %Coherence block (number of channel uses)
sigma2B = 10^(-9.6-3); %Total noise power (B*sigma2 in W)

%Traffic assumptions (From Table 2)
zetaDL = 0.6; %Fraction of downlink transmission
zetaUL = 0.4; %Fraction of uplink transmission

%Relative lengths of pilot sequences (From Table 2)
tauUL = 1; %Relative pilot length in the downlink
tauUL = 1; %Relative pilot length in the uplink

%Hardware characterization (From Table 2)
etaDL = 0.39; %PA efficiency at the BSs
etaUL = 0.3; %PA efficiency at the UEs
L_BS = 12.8e9; %Computational efficiency at BSs (flops/W)
L_UE = 5e9; %Computational efficiency at UEs (flops/W)
P_FIX = 18; %Fixed power consumption (control signals, backhaul, etc.) (W)
P_SYN = 2; %Power consumed by local oscillator at a BS (W)
P_BS = 1; %Power required to run the circuit components at a BS (W)

```

```

P_UE = 0.1; %Power required to run the circuit components at a UE (W)
P_COD = 0.1e-9; %Power required for channel coding (W/(bit/s))
P_DEC = 0.8e-9; %Power required for channel decoding (W/(bit/s))
P_BT = 0.25e-9; %Power required for backhaul traffic (W/(bit/s))

%System parameters computed from the parameters defined above
eta = 1/(zetaDL/etaDL + zetaUL/etaUL); %Effective PA efficiency, averaged over uplink and downlink.
Defined in Eq. (19)
S_x = (d_max^(kappa+2)-d_min^(kappa+2))/dbar/(1+kappa/2)/(d_max^2-d_min^2); %Average inverse channel
attenuation in the single-cell scenario (see Eq. (3))

Bsigma2SxetaSinglecell = sigma2B*S_x/eta; %Precomputation of B*sigma^2*S_x/eta for the single-cell
scenario. This term appears in Eq. (19) and other places that defines the total RF power
Bsigma2SxetaMulticell = 1.602212311888643; %Value for B*sigma^2*S_x/eta in the multi-cell scenario,
computed numerically. This term appears in Eq. (19) and other places that defines the total RF power

%%The rest of the script takes care of plotting the results.

%Density of the lines that are used in the 3d plots to make it easier to
%see the shape
gridDensity = 25;

%Plot Figure 3: Energy efficiency (in Mbit/Joule) with ZF processing in
%the single-cell scenario with perfect CSI.
figure(3); hold on; box on;
title('Figure 3: ZF processing, Single-cell, Perfect CSI')

surface(1:Kmax,1:Mmax,EEoptZF/1e6,'EdgeColor','none'); %Plot the 3d surface
colormap(autumn);

%Compute and plot the optimal point
[EEvalues,indM] = max(EEoptZF,[],2);
[EEoptimal,indK] = max(EEvalues);
plot3(indM(indK),indK,EEoptimal/1e6,'k*', 'MarkerSize',10);

if runSequentialAlgorithm == true
plot3(K_sequential(1:itrSequential),M_sequential(1:itrSequential),EE_sequential(1:itrSequential)/1e6, 'k-');
end

%Plot lines on top of the 3d surface, to make it easier to see the shape
for m = [1 gridDensity:gridDensity:Mmax]
plot3(1:Kmax,m*ones(1,Kmax),EEoptZF(m,:)/1e6,'k-');
end

for k = [1 gridDensity:gridDensity:Kmax]
plot3(k*ones(1,Mmax),1:Mmax,EEoptZF(:,k)/1e6,'k-');
end

plot3(1:Kmax,1:Kmax,zeros(Kmax,1),'k-');

view([-46 24]);
axis([0 Kmax 0 Mmax 0 35]);

ylabel('Number of Antennas (M)');
xlabel('Number of Users (K)');
zlabel('Energy Efficiency [Mbit/Joule]');

if runMonteCarloSimulationsMMSE == true

```

```

%Plot Figure 4: Energy efficiency (in Mbit/Joule) with MMSE processing in
%the single-cell scenario with perfect CSI.
figure(4); hold on; box on;
title('Figure 4: MMSE processing, Single-cell, Perfect CSI');

surface(1:Kmax,1:Mmax,EEoptMMSE/1e6,'EdgeColor','none'); %Plot the 3d surface
colormap(autumn);

%Compute and plot the optimal point
[EEvalues,ind] = max(EEoptMMSE,[],2);
[EEoptimal, ind2] = max(EEvalues);
plot3(ind(ind2),ind2,EEoptimal/1e6,'k*', 'MarkerSize',10);

%Plot lines on top of the 3d surface, to make it easier to see the shape
for m = [1 gridDensity:gridDensity:Mmax]
    plot3(1:Kmax,m*ones(1,Kmax),EEoptMMSE(m,:)/1e6,'k-');
end

for k = [1 gridDensity:gridDensity:Kmax]
    plot3(k*ones(1,Mmax),1:Mmax,EEoptMMSE(:,k)/1e6,'k-');
end

view([-46 24]);
axis([0 Kmax 0 Mmax 0 35]);

ylabel('Number of Antennas (M)');
xlabel('Number of Users (K)');
zlabel('Energy Efficiency [Mbit/Joule]');

end

if runMonteCarloSimulationsMRT == true

%Plot Figure 5: Energy efficiency (in Mbit/Joule) with MRT/MRC processing in
%the single-cell scenario with perfect CSI.
figure(5); hold on; box on;
title('Figure 5: MRT/MRC processing, Single-cell, Perfect CSI');

surface(1:Kmax,1:Mmax,EEoptMRT/1e6,'EdgeColor','none'); %Plot the 3d surface
colormap(autumn);

%Compute and plot the optimal point
[EEvalues,ind] = max(EEoptMRT,[],2);
[EEoptimal, ind2] = max(EEvalues);
plot3(ind(ind2),ind2,EEoptimal/1e6,'k*', 'MarkerSize',10);

%Plot lines on top of the 3d surface, to make it easier to see the shape
for m = [1 gridDensity:gridDensity:Mmax]
    plot3(1:Kmax,m*ones(1,Kmax),EEoptMRT(m,:)/1e6,'k-');
end

for k = [1 gridDensity:gridDensity:Kmax]
    plot3(k*ones(1,Mmax),1:Mmax,EEoptMRT(:,k)/1e6,'k-');
end

view([-46 24]);
axis([0 Kmax 0 Mmax 0 12]);

ylabel('Number of Antennas (M)');
xlabel('Number of Users (K)');
zlabel('Energy Efficiency [Mbit/Joule]');

end

```

```

%Plot Figure 6: Energy efficiency (in Mbit/Joule) with ZF processing in
%the single-cell scenario with imperfect CSI.
figure(6); hold on; box on;
title('Figure 6: ZF processing, Single-cell, Imperfect CSI')

surface(1:Kmax,1:Mmax,EEoptZFimperfect/1e6,'EdgeColor','none'); %Plot the 3d surface
colormap(autumn);

%Compute and plot the optimal point
[EEvalues,indM] = max(EEoptZFimperfect,[],2);
[EEoptimal,indK] = max(EEvalues);
plot3(indM(indK),indK,EEoptimal/1e6,'k*','MarkerSize',10);

%Plot lines on top of the 3d surface, to make it easier to see the shape
for m = [1 gridDensity:gridDensity:Mmax]
    plot3(1:Kmax,m*ones(1,Kmax),EEoptZFimperfect(m,:)/1e6,'k-');
end

for k = [1 gridDensity:gridDensity:Kmax]
    plot3(k*ones(1,Mmax),1:Mmax,EEoptZFimperfect(:,k)/1e6,'k-');
end

plot3(1:Kmax,1:Kmax,zeros(Kmax,1),'k-');

view([-46 24])
axis([0 Kmax 0 Mmax 0 30])

ylabel('Number of Antennas (M)');
xlabel('Number of Users (K)');
zlabel('Energy Efficiency [Mbit/Joule]');

%Placeholders for storing the EE-optimal sum rates for different M and for
%each processing scheme.
optEEsumratesZF = zeros(Mmax,1);
optEEsumratesMRT = zeros(Mmax,1);
optEEsumratesMMSE = zeros(Mmax,1);
optEEsumratesZFimperfect = zeros(Mmax,1);

%Go through all different M
for M = 1:Mmax

%Store the maximal EE for different number of antennas M (normalized to Mbit/Joule)
optEEsZF(M) = EEoptZF(M,optKzf(M))/1e6;
optEEsMRT(M) = EEoptMRT(M,optKmrt(M))/1e6;
optEEsMMSE(M) = EEoptMMSE(M,optKmmse(M))/1e6;
optEEsZFimperfect(M) = EEoptZFimperfect(M,optKzfimperfect(M))/1e6;

%Store the corresponding EE-optimal RF power
optRFPowersZF(M) = RFpowersZF(M,optKzf(M));
optRFPowersMRT(M) = RFpowersMRT(M,optKmrt(M));
optRFPowersMMSE(M) = RFpowersMMSE(M,optKmmse(M));
optRFPowersZFimperfect(M) = RFpowersZFimperfect(M,optKzfimperfect(M));

%Store the corresponding EE-optimal sum rates (normalized to Gbit/s)
optEEsumratesZF(M) = sumRatesZF(M,optKzf(M))/1e9;
optEEsumratesMRT(M) = sumRatesMRT(M,optKmrt(M))/1e9;
optEEsumratesMMSE(M) = sumRatesMMSE(M,optKmmse(M))/1e9;
optEEsumratesZFimperfect(M) = sumRatesZFimperfect(M,optKzfimperfect(M))/1e9;

end

%Compute and store the value of M that maximizes the EE globally. It is
%used to draw circles at the optimal values in Figures 11-13.
[~,OptimalReuse1] = max(optEEsMulticellReuse1);
[~,OptimalReuse2] = max(optEEsMulticellReuse2);
[~,OptimalReuse4] = max(optEEsMulticellReuse4);

```

```

%Plot Figure 11: Maximal EE in the multi-cell scenario for different number
%of antennas.
figure(11); hold on; box on;
title('Figure 11: Multi-cell, Comparison of EE values');

plot(Mrange,optEEsMulticellReuse4,'b--','LineWidth',1);
plot(Mrange,optEEsMulticellReuse2,'k','LineWidth',1);
plot(Mrange,optEEsMulticellReuse1,'r-.','LineWidth',1);

plot(MoptimalReuse4,optEEsMulticellReuse4(MoptimalReuse4),'bo','LineWidth',1);
plot(MoptimalReuse2,optEEsMulticellReuse2(MoptimalReuse2),'ko','LineWidth',1);
plot(MoptimalReuse1,optEEsMulticellReuse1(MoptimalReuse1),'ro','LineWidth',1);

axis([0 Mmax 0 8]);

legend('ZF (Imperfect CSI): Reuse 4','ZF (Imperfect CSI): Reuse 2','ZF (Imperfect CSI): Reuse
1','Location','SouthEast');

xlabel('Number of Antennas (M)');
ylabel('Energy Efficiency [Mbit/Joule]');

%Plot Figure 12: Total RF power at the EE-maximizing solution in the
%multi-cell scenario for different number of antennas. The radiated power per
%BS antennas is also shown.
figure(12); hold on; box on;
title('Figure 12: Multi-cell, Comparison of RF power and radiated power/antenna')

plot(Mrange,optRFpowersMulticellReuse4,'b--','LineWidth',1);
plot(Mrange,optRFpowersMulticellReuse2,'k','LineWidth',1);
plot(Mrange,optRFpowersMulticellReuse1,'r-.','LineWidth',1);

plot(MoptimalReuse4,optRFpowersMulticellReuse4(MoptimalReuse4),'bo','LineWidth',1);
plot(MoptimalReuse2,optRFpowersMulticellReuse2(MoptimalReuse2),'ko','LineWidth',1);
plot(MoptimalReuse1,optRFpowersMulticellReuse1(MoptimalReuse1),'ro','LineWidth',1);

plot(Mrange,zetaDL*eta*optRFpowersMulticellReuse1./Mrange,'r-.','LineWidth',1);
plot(Mrange,zetaDL*eta*optRFpowersMulticellReuse2./Mrange,'k','LineWidth',1);
plot(Mrange,zetaDL*eta*optRFpowersMulticellReuse4./Mrange,'b--','LineWidth',1);

plot(MoptimalReuse4,zetaDL*eta*optRFpowersMulticellReuse4(MoptimalReuse4)./MoptimalReuse4,'bo','LineWi
dth',1);
plot(MoptimalReuse2,zetaDL*eta*optRFpowersMulticellReuse2(MoptimalReuse2)./MoptimalReuse2,'ko','LineWi
dth',1);
plot(MoptimalReuse1,zetaDL*eta*optRFpowersMulticellReuse1(MoptimalReuse1)./MoptimalReuse1,'ro','LineWi
dth',1);

set(gca,'YScale','Log');
axis([0 Mmax 1e-2 1e2]);

text(20,5.5,'Total RF power');
text(20,0.15,'Radiated power per BS antenna');
legend('ZF (Imperfect CSI): Reuse 4','ZF (Imperfect CSI): Reuse 2','ZF (Imperfect CSI): Reuse
1','Location','Best');

xlabel('Number of Antennas (M)');
ylabel('Average Power [W]');

%Plot Figure 13: Area throughput at the EE-maximizing solution in the
%multi-cell scenario, for different number of BS antennas.
figure(13); hold on; box on;
title('Figure 13: Multi-cell, Comparison of area throughput')

```

```

plot(Mrange,optEEsumratesMulticellReuse4/areaMulticell,'b--','LineWidth',1);
plot(Mrange,optEEsumratesMulticellReuse2/areaMulticell,'k','LineWidth',1);
plot(Mrange,optEEsumratesMulticellReuse1/areaMulticell,'r-.','LineWidth',1);

plot(MoptimalReuse4,optEEsumratesMulticellReuse4(MoptimalReuse4)/areaMulticell,'bo','LineWidth',1);
plot(MoptimalReuse2,optEEsumratesMulticellReuse2(MoptimalReuse2)/areaMulticell,'ko','LineWidth',1);
plot(MoptimalReuse1,optEEsumratesMulticellReuse1(MoptimalReuse1)/areaMulticell,'ro','LineWidth',1);

axis([0 Mmax 0 9]);

legend('ZF (Imperfect CSI): Reuse 4','ZF (Imperfect CSI): Reuse 2','ZF (Imperfect CSI): Reuse 1','Location','NorthWest');

xlabel('Number of Antennas (M)');
ylabel('Area Throughput [Gbit/s/km^2]');

%Plot Figure 14: Energy efficiency (in Mbit/Joule) with ZF processing
%in multi-cell scenario with pilot reuse 4.
figure(14); grid on; hold on;
title('Figure 14: ZF processing, Multi-cell, Pilot reuse 4')

surface(1:Kmax,1:Mmax,EEoptZFMulticellReuse4(1:Mmax,:)/1e6,'EdgeColor','none'); %Plot the 3d surface
colormap(autumn);

%Compute and plot the optimal point
[EEvalues,indM] = max(EEoptZFMulticellReuse4,[],2);
[EEoptimal,indK] = max(EEvalues);
plot3(indM,indK,EEoptimal/1e6,'k*','MarkerSize',10);

%Plot lines on top of the 3d surface, to make it easier to see the shape
for m = [1 gridDensity:gridDensity:Mmax]
    plot3(1:Kmax,m*ones(1,Kmax),EEoptZFMulticellReuse4(m,:)/1e6,'k-');
end

for k = [1 gridDensity:gridDensity:Kmax]
    plot3(k*ones(1,Mmax),1:Mmax,EEoptZFMulticellReuse4(:,k)/1e6,'k-');
end

plot3(1:Kmax,1:Kmax,zeros(Kmax,1),'k-');

view([-46 24])
axis([0 Kmax 0 Mmax 0 8])

ylabel('Number of Antennas (M)');
xlabel('Number of Users (K)');
zlabel('Energy Efficiency [Mbit/Joule]');

```